

# NTH-149

BR/PAR30 Shroud

Lamp: 75W BR/PAR30

Type \_\_\_\_\_

Project \_\_\_\_\_

Catalog No. \_\_\_\_\_

Notes \_\_\_\_\_

## PRODUCT DESCRIPTION

Line voltage BR/PAR Shroud fixture. Yoke provides full adjustment of light source for special aiming and dual tightening knob assure lock on angle position.

## FEATURES

- Deep drawn steel socket cup housing for high strength and rigidity
- Heat resistant Teflon coated wire lead
- Low profile gimbal ring with minimal profile
- Adjustable yoke for custom aiming
- High-strength stainless steel electrical contacts
- One or two circuit track capable
- Accepts LED lamps

## CONSTRUCTION

**Housing Socket Cup:** 0.035" Deep drawn steel construction with simple, cylindrical design. All edges are softened for aesthetic appearance.

**Gimbal Ring:** 0.030" Baked enamel finished steel ring with dual brackets spot welded to socket cup enclosure.

**Yoke:** 0.085" Rigid steel "wishbone" yoke connects fixture housing to electrical contact head. Dual semi tubular rivets and friction washers provide secure hold for vertical angle.

## ELECTRICAL SYSTEM

**Socket:** Porcelain jacketed aluminum screw thread medium-base socket

**Wiring:** Teflon coated wire lead connects socket and housing to electrical contact head. Teflon coating is durable and resists heat degradation from lamp and housing radiation.

**Lamp:** 75W BR/PAR30 Maximum (not included)

## OPTIONAL ACCESSORIES

**NT-339:** BR/PAR30 Black Barn Door

**NT-342:** BR/PAR30 Black Louver (requires NT-339 or NT-345)

**NT-345:** BR/PAR30 Black Accessory Holder

## ONE/TWO CIRCUIT CONVERSION


Positive contact (opposite neutral and ground contacts) is preset to "down" position at factory but may be raised to the higher position to install onto the second circuit of Nora Lighting NT- 2300 series two-circuit track.

## LABELS AND LISTINGS

UL Listed



## PRODUCT IMAGES AND DIMENSIONS



## BR/PAR38 Shroud

Finish	Track Adapter
<b>NTH-149B</b> = Black	<b>(blank)</b> = H-Style
<b>NTH-149S</b> = Silver	<b>/J</b> = J-Style
<b>NTH-149W</b> = White	<b>/L</b> = L-Style

## Optional Accessories

Description
<b>NT-339</b> = BR/PAR30 Barn Door, Black
<b>NT-342</b> = BR/PAR30 Louver, Black (Requires NT-339 or NT-345)
<b>NT-345</b> = BR/PAR30 Accessory Holder, Black

Example: **NTH-149B** = BR/PAR30 Shroud, Black Finish, H-Style Adapter